



# 6 Zone Mixer with Voice Recorder

## T-6245



### Features

- \* Mixer with 6 zone speaker selector for source selection and zone control.
- \* Built-in mic and recorder for easy voice message recording and storage.
- \* 3 audio sources direct selection on front panels.
- \* 6 zone selection buttons on front panel.
- \* 6 zone paging console work together with the mixer through RJ45 port for remote control and announcement.
- \* Mic input by XLR type with phantom power and gain control.
- \* 3 aux inputs for tape, CD and tuner.
- \* Built-in chime, whose remote trigger and volume is provided.
- \* 3 voice messages broadcast in continuous and once modes.
- \* 3 channel pre outputs: music, music/page and page.
- \* 6 zone line outputs for power amplifier.
- \* Volume control is provided for mic, music, mater, record and message broadcast, plus bass and treble tone control.
- \* Indications include zone selector, source selector, record state, power and output level meters.
- \* 4 levels of priority from high to low: remote paging console, Mic1, chime, pre-recorded message broadcast.

### Specifications

<b>Model</b>	T-6245
<b>CONSOLE INPUT</b>	
<b>Sensitivity</b>	5 mV/600Ω, 500mV/10KΩ
<b>S/N Ratio</b>	>68dB
<b>Frequency Response</b>	50Hz~17KHz (+1, -3dB)
<b>MIRCOPHONE INPUT</b>	
<b>Sensitivity</b>	5 mV/600Ω, 500mV/10KΩ
<b>S/N Ratio</b>	>68dB
<b>Frequency Response</b>	50Hz~17KHz (-3dB)
<b>Phantom Power</b>	+48V
<b>3 AUXILIARY INPUTS</b>	
<b>Tuner and Tape Input Sensitivity/Impedance</b>	200mV/47Ω
<b>CD Input Sensitivity/Impedance</b>	500mV/47Ω
<b>S/N Ratio</b>	>90dB
<b>Frequency Response</b>	20Hz~20KHz (+1, -3dB)
<b>CONTROL</b>	
<b>Bass</b>	±12dB at 100Hz
<b>Treble</b>	±12dB at 10KHz
<b>Chime</b>	2 tone active for contact free in priority and BGM
<b>Normal Distortion</b>	>0.05%
<b>OPERATING CONDITION</b>	
<b>Power Supply</b>	~110V-230V 50/60Hz & DC 24V
<b>Dimensions</b>	484 x 303 x 88mm
<b>Weight</b>	6.32Kg
<b>Max number of paging console</b>	6

### Rear Panel

